EDGE 10703 ZINS-9A023-00 LHR Door thickness 1-15/16" (50mm) 9 Door thickness
1-1/4"-51mm) Per exit device instructions DOOR 7/8"(22mm) 1-3/4"(44.5mm) OR 2-TAP 1/4"-20 UNC 3-DRILL 1/2" DIA-LATCH EDGE 1-3/4"(44.5mm) OR 9 DOOR 0 INSIDE **OUTSIDE** 0 OF DOOR OF DOOR 0 TO FINISHED FLOOR 40-5/16" (1024mm) 3-Ø 1/2" RIM/VERTICAL TYPE PANIC EXIT DEVICE (12.7mm)Installation instructions for changing lever handing 2-1/4"-20UNC (3) 1 Step 3: Put the reversed handle back. Step 4: Step 1: Tighten set screw Remove set screw by Step 2: by hex wrench. hex wrench. Place lever in reverse direction.